

RGL Lightbar Series Software Update Details

Version: 3.3

Release Date: 07/17/05

Download and Installation Instructions

Download this firmware only if the version you are presently using is less than 3.3. The lightbar firmware revision level will appear on the right side of the display when lightbar is initially powered. The firmware version will begin with an asterisk, followed by the version level. For example, if the lightbar displays *32 on the right hand display, this would indicate a firmware version of 3.3 in the lightbar.

Important: To upgrade firmware in the RGL500/600, you must have the proper lightbar upgrade cable (Raven P/N 117-0159-983), which is not included with the purchase of an RGL500/600. USB to DB9 serial adapters will not work with this update. A dedicated DB9 serial port is required to complete this update.

Before downloading file, create a folder on the hard drive of your computer, such as "RGL 3.3". Click here to receive the latest firmware version for the RGL500/600. When the "File Download" window appears, ensure "Save File to Disk" is checked. Click "OK". Select the folder previously created to download the file to. Once file is downloaded, open the folder on the hard drive and run the "LbPrg" program. A "Help" menu is provided when the program is open for additional assistance.

***NOTE: Please print out the Light Bar Update Procedure included in the zip file (Light Bar update instructions.doc)